




## RemoteCam8™ Series Product Specification

Updated: 12/2/2024



Sound Control Technologies (SCT) Camera Extension Kits are designed to streamline the installation of digital video PTZ camera systems. By simplifying complex cabling and extending traditional distance limitations up to 100m, SCT's extension kits provide integrators with cost and time saving solutions.

### KEY FEATURES

- Extends power to cameras and assembly (no factory camera PSU required), PTZ control, dual video, and dual channel audio over a CAT6 cable between 10m-100m.
- Dual HDMI Distribution Amplifier on each HDMI channel.
- Ethernet controlled PTZ camera support.
- Simple Plug & Play installation, no programming required.
- Two port Ethernet switch at RC8-HE™ Head End Module for control expansion.
- Selectable ARC/Analog sends audio to Cisco Quad Camera speaker via existing HDMI channel.
- Allows pass-through of manufacturer firmware updates from codec to camera.
- All hardware-specific camera and codec connection cables included.
- PowerSniffer included for testing SCTLink™ cable conductor continuity.
- Integrator only required to provide a CAT6 SCTLink™ Cable.

### TECHNICAL SPECS

- Video Format: HDMI, up to 1920x1080p@60Hz, 2x dual buffered outputs with HDCP support.
- HDMI Connectors (RC8-CE™): Two Independent HDMI Inputs
- HDMI Connectors (RC8-HE™): Two Sets of Independent 1x2 DA HDMI Outputs

- Audio In/Out (RC8-CE™): 3.5mm TRS Jacks, Stereo Line Level Unbalanced
- ARC Analog Audio In (RC8-HE™): 3.5mm TRS Jack, Stereo Line Level Unbalanced
- Ethernet Connectivity (RC8-CE™): Single 10/100 Port
- Ethernet Connectivity (RC8-HE™): 10/100 Two Port Layer 2 Ethernet Switch
- Power Out (RC8-CE™): 4 Pin-Din

### SCTLINK™ CABLE SPECS

SCT requires CAT6 or better shielded cable for the SCTLink™.

Proper termination and testing, along with good cable management, minimizes potential problems.

**Wiring Termination Standard** T568A or T568B  
10m Minimum - 100m Maximum Length

**Power Consumption** A linked kit will consume 17W, plus the power consumption of attached camera.

### MODULE & POWER SUPPLY SPECS

#### RC8-CE™ Camera End Module

- Imperial Dims: H: 1.6" x W: 7.35" x D: 4.35"
- Metric Dims: H: 40mm x W: 186mm x D: 110mm
- Weight: 0.9 lbs / 408g

#### RC8-HE™ Head End Module

- Imperial Dims: H: 1.34" x W: 9.04" x D: 5.32"
- Metric Dims: H: 34mm x W: 229mm x D: 135mm
- Weight: 1.2 lbs / 544g

#### WPS-48™ Power Supply (Included)

- Imperial Dims: H: 1.0" x W: 2.98" x D: 5.96"
- Metric Dims: H: 25mm x W: 75mm x D: 151mm
- Weight: 0.84 lbs / 380g

- Input: 100 to 240VAC, 50Hz-60Hz, 1.8A Max
- Output: 48VDC, 2.5A Max
- Output Connector: 3 Pin-Din
- Regulatory Approvals: UL, CE, FCC, CCC, TÜV, RCM & RoHS

## SUPPORTED DEVICES

[www.soundcontrol.net/products/camera-extension-kits/remotecam8-platform](http://www.soundcontrol.net/products/camera-extension-kits/remotecam8-platform)

### Cameras

Cisco Quad Camera

### Codecs

Cisco SX80, Codec Plus & Codec Pro

## CAMERA-SPECIFIC MOUNTS

### RC-CUBBY™ Series On-Wall Mounts

<https://www.soundcontrol.net/products/camera-mounts/rc-cubby-on-wall-mounts>

- Integrate mounting of the camera and the RC8-CE™ Camera End Module.
- All-metal solution with a common backbox and bezel.
- Camera plates are laser cut to match the contour of the camera base.
- Boasts an extremely clean look with a simple one-person installation technique and easy cable management.

## RACK SHELVES

### RC-RKM™ 2RU 12" Deep Rack Shelf

[www.soundcontrol.net/product/rc-rkm-rack-shelf](http://www.soundcontrol.net/product/rc-rkm-rack-shelf)

- Included in all RemoteCam<sup>8</sup>™ Kits to ensure proper ventilation for the RC8-HE™.
- Designed to mount the RCU2-HE™, RC4-HE™, RC5-HE™, RC6-HE™, RC7-HE™, RC8-HE™, RTK-RX™ and RC-SDA™ modules, specific manufacturer codecs, and power supplies.
- Leaves access to rear of modules for clean and easy cabling.

## PRODUCT WARRANTIES

[www.soundcontrol.net/support](http://www.soundcontrol.net/support)

**Included:** 3 Year Standard  
Advance Replacement  
Limited Warranty

**Available:** 2 Year Extended  
Advance Replacement  
Limited Warranty



## SOLUTION FINDER

Not sure where to start? Try our Solution Finder!  
[www.soundcontrol.net/solution-finder](http://www.soundcontrol.net/solution-finder)

